

control box led					
station	power led red color	connect led green color	charge led blue color	faulty led yellow color	reason
1	on	off	off	off	have power but not connect
2	on	on	off	off	connect but not charger
3	on	on	flash	off	charging
4	on	on	on	off	charged completely
5	on	on	off	on	communication error
6	on	flash	flash	off	overload protection
7	on	on	flash	on	abnormal current(Short Circuit Protection)
8	on	flash	flash	on	leakage protection
9	on	off	off	flash	over voltage or less voltage protection
10	on	on	on	on	overheating protection